



Print head fy41 for Kingroon KP3S



Yohei Fukuma

[VIEW IN BROWSER](#)

updated 2. 7. 2023 | published 2. 7. 2023

Summary

Lightweight print head to fix Dragon Hotend, Sherpa-mini, 3010 / 5015x2 Fan and Panasonic GX-H8A or B for Kingroon KP3S

[3D Printers](#) > [3D Printers - Upgrades](#)

I designed and shared a lightweight print head mounter to fix V6Hotend, Sherpa-mini, 3010 Hotend Fan, 5015x2 Section Fan and Panasonic GX-H8A or B Probe for Kingroon KP3S. An X belt tension adjustment mechanism, X head position fine adjustment mechanism, and acceleration sensor board mounting hole are also provided on the back of the print head.

Some parts are M3 tapped, so we recommend purchasing a tap drill set even if it is inexpensive.

Reference URL(JPN): <https://amzn.to/43nC3Xj>

Processing example: https://www.youtube.com/watch?v=5AMY5ZxE_U4

It seems that the following screws are used except for the Sherpa-mini part, so I designed it so that it can be distributed and covered with a general button bolt set.

Reference URL(JPN): <https://amzn.to/445JB20>

M3x8 3pcs

M3x10 4pcs

M3x12 1pcs

M3x14 2pcs

M3x16 4pcs

M3x18 6pcs
M3x20 5pcs
M3nut 3pcs
M3insert nut 5pcs

The description of [probe] on Klipper by attaching Panasonic GX-H8A or B is as follows.

Reference URL(JPN): <https://www.monotaro.com/p/4711/0427/>

[probe]

Inductive Probe - If you use this section , please comment the [bltouch] section

pin: ^!PC4 # Added "!" for non-proximity ON, no ! for non-proximity OFF. ^ is a pull-up specification (when turned ON - connected sensor)

x_offset: 0 # X distance between nozzle and sensor

y_offset: -19.4 # Y distance between nozzle and sensor

samples: 2 # number of samples for each point

samples_result: median # how each sample is calculated:

median=median, average=average

sample_retract_dist: 1.0 # Height (mm) to lift the tool head between each sample. Detection does not turn off unless distance is taken by the sensor

samples_tolerance: 0.006 # Tolerance between samples (mm). Retry operation when the variation exceeds this value.

samples_tolerance_retries: 2 # number of sample retries

z_offset: 1.2 # Increasing the value moves the nozzle closer to the bed.

For details on installing probes, please refer to Eitoku's article below.

(JPN) https://note.com/eitoku_note/n/n0dcc3f176f32

Moyashi's article below is recommended for adjusting Klipper using the accelerometer.

(JPN) http://hitoriblog.com/kingroon_kp3s/docs/tuning_klipper_using_an_accelerometer/

Kishi Sangyo's article below is recommended for the entire review of Klipper's printer.cfg.

(JPN) <https://note.com/tcbjr8d/n/nf9b6892c5f1a>

For the Sherpa-mini part, he will be a wonderful extruder created by Annex-Engineering. Please refer to the following for reference, reuse, and redistribution of various data such as 3D data.

You should must use the short arm.

https://github.com/Annex-Engineering/Sherpa_Mini-Extruder

<https://store.annex.engineering/>

<https://discord.gg/MzTR3zE>

<https://github.com/Annex-Engineering/ANNEX-Engineering-License-Agreement/blob/main/LICENSE.md>

(Original Japanese)

Kingroon KP3S Dragon Hotend, Sherpa-mini, 3010 Hotend Fan 5015
Section Fan, Panasonic GX-H8A or B Probe

X

X

M3

URL:<https://amzn.to/43nC3Xj>

:https://www.youtube.com/watch?v=5AMY5ZxE_U4

Sherpa-mini

URL:<https://amzn.to/445JB20>

M3x8 3pcs

M3x10 4pcs

M3x12 1pcs

M3x14 2pcs

M3x16 4pcs

M3x20 5pcs

M3nut 1pcs

M3insert nut 4pcs

Panasonic GX-H8A or B

Klipper [probe]

URL:<https://www.monotaro.com/p/4711/0427/>

[probe]

Inductive Probe - If you use this section , please comment the
[bltouch] section

pin: ^!PC4 # ON "!" OFF ! ^ (ON -)

x_offset: 0 # X

y_offset: -19.4 # Y

samples: 2 #

samples_result: median # : median= average=

sample_retract_dist: 1.0 # (mm) OFF

samples_tolerance: 0.006 # (mm)

samples_tolerance_retries: 2 #

z_offset: 1.2 #

Eitoku

https://note.com/eitoku_note/n/n0dcc3f176f32

Klipper moyashi

http://hitoriblog.com/kingroon_kp3s/docs/

[tuning_klipper_using_an_accelerometer/](#)

Klipper printer.cfg

<https://note.com/tcbjr8d/n/nf9b6892c5f1a>

https://github.com/Annex-Engineering/Sherpa_Mini-Extruder

<https://store.annex.engineering/>

<https://discord.gg/MzTR3zE>

<https://github.com/Annex-Engineering/ANNEX-Engineering-License-Agreement/blob/main/LICENSE.md>

This remix is based on



Print head fy36 for Kingroon KP3S

by Yohei Fukuma

Model files



pusher-x-limit-kp3s-fy41-v8-export.stl



housing-front-sherpa-mini-5015-fan-x2b-v5-export.stl



holder-dual-5015-fan-fy41-export.stl



holder-dragon-kp3s-fy41-export.stl



duct-partsfan-fy41-5015x2dragon-v6-export.stl



duct-partsfan-fy41-5015x2dragon-v4.f3d



print-head-fy41-sherpagxh8dragon5015x2-v33-kp3s.step

License

This work is licensed under a
Creative Commons (4.0 International License)



Attribution—Noncommercial—Share Alike

-
- ✗ | Sharing without ATTRIBUTION
 - ✓ | Remix Culture allowed
 - ✗ | Commercial Use
 - ✗ | Free Cultural Works
 - ✗ | Meets Open Definition